

## Palco Low Voltage

Design Artec  
Studio


iGuzzini

Last information update: March 2025

### Product configuration: RC80+GOBO10B

RC80: Palco LV spotlight Ø 37 - Framer - BLUETOOTH

GOBO10B: Gobo ø10mm - min focusing



### Product code

RC80: Palco LV spotlight Ø 37 - Framer - BLUETOOTH

### Technical description

Miniaturised adjustable projector spotlight with adapter for installation on 48V low voltage track. The adapter made of a thermoplastic material includes the DC/DC driver circuit and Bluetooth protocol. Die-cast aluminium technical body for LED lamp; high definition OptiBeam reflector. The aluminium optical assembly includes a sophisticated telecentric optics system consisting of four anti-reflection-treated glass lenses. Black anodised aluminium locknut for manual focusing. The innovative optical system, combined with the option of manual adjustment and four shaping flaps, allows precise, well-defined wall lighting with no halo effects or soft edges. The optical assembly is fixed to the technical body with a rapid and practical magnetic system. This solution allows it to be rotated by 360° which increases its versatility considerably. The projector is designed to obtain a square, rectangular or variously irregular beam by manoeuvring the flaps. The package includes two gobos for circular shapes. A rapid tool-free system for connecting the adapter electrically and mechanically to the track. Luminaire with Bluetooth Low Energy technology (WiSilica). Frequency 2.4 GHz BLE. The luminaire can be controlled with the Quick BLE system and Smart Light Control app that enable on-off, dimming and scene recall functions. The app is available on the Apple Store and Google Play Store. It can be integrated in the system's "Mesh" network that allows multiple luminaires to be controlled. OTA (over the air) update via app. Integrated Beacon that can be activated via Smart Light Control (Eddystone, iBeacon, Alt Beacon) that enables functions including push notification and indoor navigation-wayfinding.

### Installation

An adapter is used to fix the device mechanically and tool-free to the 48V track. Max luminaire-luminaire distance (\*): 8 m; max smartphone-luminaire distance (\*): 20 m.

### Colour

White (01) | Black (04)

### Weight (Kg)

0.19

### Mounting

Low voltage track

### Wiring

Direct connection on 48V track. Track power supply unit to be ordered separately. Luminaire can be controlled with Bluetooth technology (WiSilica)

### Notes

(\*) The maximum distance for Bluetooth installations is affected by physical obstacles, like walls, metal panels and the layout of the system. We suggest that a test is conducted at the installation site.

Complies with EN60598-1 and pertinent regulations



### Technical data

Im system:	143	MacAdam Step:	2
W system:	6.5	Lamp code:	LED
Im source:	750	Number of lamps for optical assembly:	1
W source:	6.5	ZVEI Code:	LED
Luminous efficiency (lm/W, real value):	21.9	Number of optical assemblies:	1
Im in emergency mode:	-	LED current [mA]:	700
Total light flux at or above an angle of 90° [Lm]:	0	Power factor:	See installation instructions
Light Output Ratio (L.O.R.) [%]:	19	Minimum dimming %:	1
CRI (minimum):	90	Control:	Bluetooth WiSilica
Colour temperature [K]:	4000		

Polar

