

LASER BLADE XS (LC)

INSTRUCTIONS SHEET

PAGE: 1 of 2


DOWNLIGHT TRIMLESS MODEL: ILBXS01 / 02 / 03 / 04 / 05 / 09 / 10 / 15 - TL - (LC) - RF - REM
WALL WASHER TRIMLESS MODEL: ILBXS03 / 05 / 10 / 15 - TL - (LC) - RF - REM

IMPORTANT - READ CAREFULLY BEFORE INSTALLING FIXTURE. RETAIN THESE INSTRUCTIONS FOR FUTURE REFERENCE.
THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE NATIONAL ELECTRICAL CODE AND ALL APPLICABLE LOCAL CODES, BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT, AND THE HAZARDS INVOLVED. PROPER GROUNDING IS REQUIRED FOR SAFETY.

REMODEL INSTALLATION (RF) WITH MOUNTING ACCESSORY (TRIMLESS FRAME) - TO REMOTE DRIVER (REM)


- A- MAKE THE CUT-OUT OPENING (**SEE DIMENSIONS BELOW**).
B- INSERT THE SPRING CLIP IN THE MOUNTING HOLES AND INSERT THE TRIMLESS FRAME IN THE CEILING. MAKE SURE THE WIRES ARE ACCESSIBLE.
C- SCREW IN THE FRAME KIT PERFORATED AREA, USING MAXIMUM #8 x 1" (25mm) SCREWS (**NOT INCLUDED**). THE TRIMLESS FRAME MUST PROTRUDE FROM THE CEILING BY 1/16" (1.6mm).

A + B



Model	Trimless frame kit	Cut-out dimensions	Ceiling thickness	Clearance
LBXS01	TK-LBXS01TL-RF	1 1/8" x 1 1/8" (29 x 29mm)	5/8" (16mm)	2" (50mm)
LBXS02	TK-LBXS02TL-RF	1 1/8" x 1 1/8" (29 x 42mm)		
LBXS03	TK-LBXS03TL-RF	1 1/8" x 2 3/8" (29 x 60mm)		
LBXS04	TK-LBXS04TL-RF	1 1/8" x 1 1/8" (48 x 48mm)		
LBXS05	TK-LBXS05TL-RF	1 1/8" x 3 3/4" (29 x 95mm)		
LBXS09	TK-LBXS09TL-RF	2 3/4" x 2 3/4" (67 x 67mm)		
LBXS10	TK-LBXS10TL-RF	1 1/8" x 7 1/4" (29 x 184mm)		
LBXS15	TK-LBXS15TL-RF	1 1/8" x 10 3/4" (29 x 274mm)		

C



LASER BLADE XS (LC)

DOWNLIGHT TRIMLESS MODEL: ILBXS01 / 02 / 03 / 04 / 05 / 09 / 10 / 15 - TL - (LC) - RF - REM
WALL WASHER TRIMLESS MODEL: ILBXS03 / 05 / 10 / 15 - TL - (LC) - RF - REM

INSTRUCTIONS SHEET

PAGE: 2 of 2

FINAL STEP

D- FINISH THE ASSEMBLY BY PLASTERING, SANDING AND PAINTING.

