



**IMPORTANT** - READ CAREFULLY BEFORE INSTALLING FIXTURE. RETAIN THESE INSTRUCTIONS FOR FUTURE REFERENCE. THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE NATIONAL ELECTRICAL CODE AND ALL APPLICABLE LOCAL CODES, BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT, AND THE HAZARDS INVOLVED. PROPER GROUNDING IS REQUIRED FOR SAFETY.

## CHICAGO PLENUM INSTALLATION (CP) INTEGRAL DRIVER (120V / 120-277V) DIMMING 0-10V (D10) - TRIAC/ELV (LTE) - DALI (DA)

- A- REMOVE (4) PHILLIPS SCREWS IN ORDER TO OPEN HOUSING.
- B- REMOVE THE KNOCKOUT, INSTALL AN AIRTIGHT CONDUIT AND A CONDUIT CONNECTOR (**NOT INCLUDED**).  
\*0-10V DIMMING FOR CHICAGO PLENUM (CP): REMOVE EXTRA KNOCKOUT PLUG, INSTALL AIR TIGHT CONDUIT AND CONDUIT CONNECTOR (**NOT INCLUDED**).
- C- CLOSE THE HOUSING BY SCREWING THE (4) PHILLIPS SCREWS PREVIOUSLY REMOVED (A). LEAVE AT LEAST 6" (152mm) OF FEEDER CABLE ACCESSIBLE FROM UNDER THE CEILING.
- D- ENGAGE (4) HANGER BARS IN HOUSING SLOTS AVAILABLE AND CONNECT THEM TOGETHER.




DOWNLIGHT TRIM MODEL: ICRY3 / 6 / 9 T - CP - 120 / UNV


E- FASTEN HANGER BARS TO CEILING BRACE WITH #8 SCREWS (**NOT INCLUDED**). HOUSING MUST BE FLUSH WITH THE BOTTOM OF THE CEILING BRACES.

F- INSTALL THE DRYWALL AND MAKE THE CUT-OUT OPENING (**SEE DIMENSIONS BELOW**).

**E**




**F**




Model	Housing	Cut-out dimensions (A x B)	Ceiling thickness	Clearance
ICRY3	BI-CRY3T-CP	2 <sup>9</sup> / <sub>16</sub> " x 7 <sup>1</sup> / <sub>16</sub> " (64.5 x 185mm)		
ICRY6	BI-CRY6T-CP	2 <sup>7</sup> / <sub>16</sub> " x 14 <sup>5</sup> / <sub>16</sub> " (64.5 x 363mm)	1/8"-1 1/8" (3-29mm)	3 5/8" (92mm)
ICRY9	BI-CRY9T-CP	2 <sup>7</sup> / <sub>16</sub> " x 21 <sup>3</sup> / <sub>16</sub> " (64.5 x 543mm)		

**CONNECTIONS**

MAKE ALL NECESSARY CONNECTIONS (SEE WIRING DIAGRAM BELOW) USING TWIST CONNECTOR (NOT INCLUDED).



**WIRING DIAGRAM**



## FIXTURE INSTALLATION

- A- INSERT THE LED DRIVER INSIDE THE INSULATION BOX.
- B- HOLD THE (2) CLIPS UPWARD AND INSERT FIXTURE INTO CUT-OUT.

A + B

