Design iGuzzini

iGuzzini

Last information update: March 2025

Product configuration: 380A.01

380A.01: SIPARIO Ø86 spotlight - CASAMBI - WideFlood - OBLens - - 18.1W 1350.9Im - 3000K - CRI 97 - White

Product code

380A.01: SIPARIO Ø86 spotlight - CASAMBI - WideFlood - OBLens - - 18.1W 1350.9lm - 3000K - CRI 97 - White

Technical description

Ø86 adjustable spotlight with adapter for installation on a base or electrified track. LED lamp with C.O.B. (Chip on board) technology, -CRI97- high colour rendering and 3000K tone.

Die-cast aluminium body with thermoplastic rear cap and front ring (Mass-Balance). The product can be rotated by 360° around the vertical axis with a mechanical lock and tilted by 90° relative to the horizontal plane. Passive heat dissipation. OptiBeam Lens optical system with WideFlood optic.

Body complete with dimmable power supply unit and Casambi protocol positioned inside the product track adapter. The components used allow the products to be controlled with the Casambi system app and components, enabling on-off, dimming and scene recall functions and allowing multiple luminaires to operate in a Casambi mesh network. 2.4 GHz bluetooth frequency. The app is available on the Apple Store and Google Play Store. Integrated Beacon that can be activated via an app (iBeacon) that enables smart functions for third party applications and the Jiminy Push Notification app.

Spotlight with Push&Go system designed to facilitate and safely accelerate the connection between product and optic accessory. Mechanically disconnecting the accessory allows it to be disengaged but not dropped. Three internal accessories and one external one can be used simultaneously. All internal accessories rotate 360° about the spotlight longitudinal axis.

0-1								
Colour White (01)		0.87	Weight (Kg) 0.87					
Mounting three circuit track								
Notes Max distance between prod The maximum distance is a		ike walls, metal panels and the layo	ut of the system.					
		Complies	s with EN60598-1 and pertinent reg					
IP20	E CA 🛞	pending						
Technical data								
Technical data Im system:	1351	Life Time LED 1:	> 50,000h - L90 - B10 (Ta 25°C					
	1351 18.1	Life Time LED 1: Lamp code:	> 50,000h - L90 - B10 (Ta 25°C LED					
Im system:			LED					
Im system: W system: Im source:	18.1 1710 16	Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical	LED					
Im system: W system: Im source: W source: Luminous efficiency (Im/W,	18.1 1710 16	Lamp code: Number of lamps for optical assembly: ZVEI Code:	LED 1 LED 1					
Im system: W system: Im source: W source: Luminous efficiency (Im/W, real value): Im in emergency mode: Total light flux at or above	18.1 1710 16	Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies: Power factor:	LED 1 LED 1 See installation instructions					
Im system: W system: Im source: W source: Luminous efficiency (Im/W, real value): Im in emergency mode: Total light flux at or above an angle of 90° [Lm]:	18.1 1710 16 74.6 - 0	Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies: Power factor: Inrush current:	LED 1 LED 1					
Im system: W system: Im source: W source: Luminous efficiency (Im/W, real value): Im in emergency mode: Total light flux at or above	18.1 1710 16 74.6 - 0	Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies: Power factor:	LED 1 LED 1 See installation instructions					
Im system: W system: Im source: W source: Luminous efficiency (Im/W, real value): Im in emergency mode: Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) [%]: Beam angle [°]:	18.1 1710 16 74.6 - 0	Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies: Power factor: Inrush current: Maximum number of	LED 1 LED 1 See installation instructions 20 A / - µs B10A: 50 luminaires B16A: 80 luminaires					
Im system: W system: Im source: Uuminous efficiency (Im/W, real value): Im in emergency mode: Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) [%]:	18.1 1710 16 74.6 - 0 79	Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies: Power factor: Inrush current: Maximum number of luminaires of this type per	LED 1 LED 1 See installation instructions 20 A / - µs B10A: 50 luminaires					

Minimum dimming %:

Overvoltage protection:

Control:

Imax=2044 cd	CIE	Lux			
90° 180°	nL 0.79 90° 94-100-100-100-79 UGR 18.1-18.1	h	d	Em	Emax
	DIN A.61	2	1.7	396	511
2000	UTE 0.79A+0.00T F*1=940	4	3.5	99	128
	F"1+F"2=996 F"1+F"2+F"3=1000 CIBSE	6	5.2	44	57
α=47°	LG3 L<3000 cd/m ² at 65' UGR<19 L<3000 cd/mq	@ ₆₅ . 8	7	25	32

2

3000

Colour temperature [K]:

MacAdam Step:

174 ø 86 186

C16A: 136 luminaires

Differential mode

Casambi

2kV Common mode & 1kV

Utilisation factors

R	77	75	73	71	55	53	33	00	DRR
K0.8	69	65	62	60	64	62	61	58	74
1.0	73	69	66	64	68	66	65	63	79
1.5	77	74	72	70	73	71	71	68	86
2.0	80	78	76	74	76	75	74	72	91
2.5	81	80	78	77	79	77	76	74	94
3.0	82	81	80	79	80	79	78	76	96
4.0	83	82	82	81	81	81	79	77	98
5.0	84	83	83	82	82	81	80	78	99

Luminance curve limit

QC	Α	G	1.15	200	00		1000		500				<-3	00				
	в		1.50				2000	0	1000	1	750		50	D		<=300		
	С		1.85						2000				100	0		500	<.	-300
85°					T		_				ſπ			1	7	-		8
75°									$\left\{ \left\{ \right. \right\}$	⊬	H	-	+	-	-	-		4
65°				-	-				1			1	-	\downarrow	-	$\overline{}$		2
55°				+	+					\mathbf{k}	\rightarrow			-				a h
45° 1	10 ²		2	3	4	5 6	٤	3 10 ³		2	3	4	5	6	8	104	cd/n	1 ²
	C0-18	0 -				_				C90	-270							

UGR diagram

Rifle	et :											
ceil/cav		0.70	0.70	0.50	0.50	0.30	0.70	0.70	0.50	0.50	0.30	
walls		0.50	0.30	0.50	0.30	0.30	0.50	0.30	0.50	0.30	0.30	
work	pl.	0.20	0.20	0.20	0.20	0.20	0.20	0.20	0.20	0.20	0.20	
Roor	n dim	8251003		viewed			viewed					
x	У		c	rosswis	е			endwise				
2H	2H	18.6	19.2	18.9	19.5	19.7	18.6	19.2	18.9	19.5	19.7	
	3H	18.5	19.1	18.8	19.3	19.6	18.5	19.1	18.8	19.3	19.0	
	4H	18.4	18.9	18.8	19.2	19.5	18.4	19.0	18.8	19.3	19.0	
	6H	18.3	18.8	18.7	19.1	19.5	18.4	18.8	18.7	19.2	19.5	
	BH	18.3	18.8	18.7	19.1	19.4	18.3	18.8	18.7	19.1	19.5	
	12H	18.3	18.7	18.6	19.1	19.4	18.3	18.7	18.7	19.1	19.4	
4H	2H	18.4	19.0	18.8	19.3	19.6	18.4	18.9	18.8	19.2	19.	
	ЗH	18.3	18.7	18.7	19.1	19.4	18.3	18.7	18.7	19.1	19.	
	4H	18.2	18.6	18.6	19.0	19.4	18.2	18.6	18.6	19.0	19.	
	6H	18.1	18.5	18.6	18.9	19.3	18.1	18.5	18.6	18.9	19.	
	BH	18.1	18.4	18.5	18.8	19.2	18.1	18.4	18.5	18.8	19.2	
	12H	18.0	18.3	18.5	18.7	19.2	18.0	18.3	18.5	18.7	19.3	
вн	4H	18.1	18.4	18.5	18.8	19.2	18.1	18.4	18.5	18.8	19.3	
	6H	18.0	18.2	18.5	18.7	19.2	18.0	18.2	18.5	18.7	19.	
	BH	17.9	18.2	18.4	18.6	19.1	17.9	18.2	18.4	18.6	19.1	
	12H	17.9	18.1	18.4	18.6	19.1	17.9	18.1	18.4	18.6	19.	
12H	4H	18.0	18.3	18.5	18.7	19.2	18.0	18.3	18.5	18.7	19.3	
	6H	17.9	18.2	18.4	18.6	19.1	17.9	18.2	18.4	18.6	19.1	
	8H	17.9	18.1	18.4	18.6	19.1	17.9	18.1	18.4	18.6	19.1	
Varia	tions wi	th the ot	oserver p	osition	at spacin	ig:						
S =	1.0H		4	.8- / 0.	3	4.0 / -8.3						
	1.5H		6.	7 / -12	.5		6.	7 / -12	.5			