

**Constant current On-Off LED driver 37W - VIN=220-240Vac / 50-60 Hz IOUT=700mA UOUT=24-48Vdc
Min. 8 LED connected Max. 12 LED connected**

Design iGuzzini

iGuzzini

Last information update: June 2024



Accessory code

MXT2: Constant current On-Off LED driver 37W - VIN=220-240Vac / 50-60 Hz IOUT=700mA UOUT=24-48Vdc Min. 8 LED connected Max. 12 LED connected

Technical description

Direct current electronic ballast, max. 37W - 700mA - Vin 220-240V ac $\pm 10\%$ - 50/60Hz - Vout =24-48V dc - Class II, SELV equivalent - screw terminals 2.5 mm²

Installation

In special cavity, with suitable IP rating. Outdoors, possibility of using IP67 Box for ballasts, code 9582

Colour

Indeterminate (00)

Weight (Kg)

0.16

Wiring

700 mA - min 8 max 12 LED

Complies with EN60598-1 and pertinent regulations

ERC

Technical data

Frequency [Hz]:	0/50/60	Maximum number of LED power supply units of this type per miniature circuit breaker:	B10A: 20 power supply units B16A: 32 power supply units C10A: 33 power supply units C16A: 54 power supply units
Current out [mA]:	700	Overvoltage protection:	2kV Common mode & 1kV Differential mode
Inrush current:	20 A / 250 μ s	Control:	On/off