

---

**Constant current power supply not dimm. IP68 30W with 2 outgoing cables L = 400 - Vin = 220 ÷ 240Vac 50 / 60Hz Iout = 700mA**

Design iGuzzini

iGuzzini

Last information update: September 2023

**Accessory code**

X120: Constant current power supply not dimm. IP68 30W with 2 outgoing cables L = 400 - Vin = 220 ÷ 240Vac 50 / 60Hz Iout = 700mA



---

**Technical description**

LED IP67 control gear - 30W - Vin=220-240VAC - IOut=700mA with outgoing cables L=500mm

**Colour**  
Indeterminate (00)

**Weight (Kg)**  
0.3

**Dimension (mm) (\*)**  
121x53x26

\* The dimensions may change according to production requirements to ensure that performance levels and installation methods are observed.

Complies with EN60598-1 and pertinent regulations



IP67



---

**Technical data**

Frequency [Hz]: 50/60

Current out [mA]: 700

Inrush current: 5 A / 50 µs

Maximum number of LED power supply units of this type per miniature circuit breaker:

B10A: 31 power supply units

B16A: 50 power supply units

C10A: 52 power supply units

C16A: 85 power supply units

Overvoltage protection:

4kV Common mode & 4kV Differential mode